



T.			U_f	I_f	U_o	U_g	I_o	S	μ	R_i	R_o	P_o	h	P_a				
			V	A	V	V	mA	mA/V	V/V	k Ω	k Ω	W	%	W				
3 A/104 B	STCE	1	4,5	1	130	-20	25	1,1	2,3	2	2	0,135	5	5				
3 A/144 A	STCE	2	4,5	1		160	-30								29	1,9	1,9	0,3
18004	Phi	2	4,4	0,97		190	maximum ($I_k = 60$ mA)											
104 D	WE	2	4,2	1	130	-20	25	1,18	2,5	2,1	0,16							

1) vide *4



3A/104B



3A/144A

Equivalents

TS 7	Phi	=	18004
3 A/144 AY	STCE	=	3 A/144 A
104 A	WE	=	104 D
104 DW	WE	=	104 D
210 A	WE	=	104 D
4104 D	STCE	=	104 D

T.	C_{ag}	C_{gf}	C_{af}
	pF	pF	pF
3 A/144 A	6,8	5,8	5,5
18004	2,5	2,9	4,5

