



| T. |  |  | U_f | I_f | $U_{tr(C)}$ | $U_{tr(L)}$ | U_p | I_o | I_p | R_{tr} | L_F | C_F |
|-------|---|---|-------|-------|---|-------------|-------|-------|-------|----------|-------|---------|
| | | | V | A | V | V | V | mA | mA | Ω | H | μF |
| GZ 40 | eur | 1 | 5 | 0,75 | $\begin{cases} 250 \\ 350 \end{cases}$ | | | 90 | | 125 | | 50 |
| GZ 41 | eur | 1 | 5 | 0,75 | $\begin{cases} 325 \\ 400 \end{cases}$ | 450 | 1250 | 70 | | 150 | 8 | 4 |
| U 5 | MOG | 2 | 5 | 1,6 | 400 | | | 45 | | | | 4 |
| U 50 | MOG | 3 | 5 | 2 | $\begin{cases} 350 \\ 350 \end{cases}$ | 550 | 1000 | 120 | | 100 | 5 | 32 |
| U 51 | MOG | 3 | 5 | 1 | 350 | | | 100 | 370 | | | |
| 5 W 4 | amer | 3 | 5 | 1,5 | $\begin{cases} 350 \\ 400 \end{cases}$ | 500 | 1400 | 100 | | 50 | 6 | 4 |
| 5 X 3 | amer | 4 | 5 | 2 | $\begin{cases} 400 \\ 1275 \end{cases}$ | | | 110 | | | | |
| 985 | amer | 5 | 5 | 0,5 | 250 | | | 50 | | | | |
| 986 | amer | 5 | 5 | 1 | 400 | | | 150 | | | | |
| 1560 | Phl | 2 | 5 | 2 | 300 | | | 135 | | | | |
| 1882 | Phl | 6 | 5 | 2 | 400 | | | 100 | | | | |
| 1883 | Phl | 6 | 5 | 1,6 | 350 | | | 120 | | | | |

Equivalents

| | | | | | |
|-------------|------------|-------------|------------|----------|--------------|
| DW 8 | Mul = 1560 | PVX 2800/44 | Tu = 1560 | RO 531 | Rtn = 1560 |
| G 1882 | Val = 1882 | R 5 | Fer = 1560 | TR 280 | Tri = 1560 |
| G 1883 | Val = 1883 | R 256 | Rec = 1560 | TR 1560 | Adz = 1560 |
| G 2005 | Val = 1560 | R 5100 | Zen = 1560 | V 30 | Fot = 1560 |
| G 5200 | Val = 1560 | R 5200 | Zen = 1560 | V 51 | Maz = GZ 40 |
| GL 4/25 | Sat = 1882 | RGN 1882 | Tlf = 1882 | V 580 | Vis = 1560 |
| GX 5200 | Val = 1882 | RGN 1883 | Tlf = 1883 | 5 W 4-G | amer = 5 W 4 |
| PVX 2800 | Tu = 1560 | RGN 2005 | Tlf = 1560 | 5 W 4-GT | amer = 5 W 4 |
| PVX 2800/41 | Tu = 1560 | | | | |

