



T.			U_f	I_f	U_{tr}	U_o	U_p	I_o	I_p	$U_{f/k}$	R_{tr}	C_F
			V	A	V	V	V	mA	mA	V	Ω	μF
CY 1	eur	1	20	0,2	$\left\{ \begin{array}{l} 127 \\ 170 \\ 170 \\ 250 \\ 250 \end{array} \right.$			75			0	8
CY 1 C	Mul	2	20	0,2				75			0	8
CY 31	eur	3	20	0,2				75			75	32
								75			0	8
					250			75		350	125	32
U 201	Maz	3	20	0,2	$\left\{ \begin{array}{l} 110 \\ 230 \end{array} \right.$	110		90			0	32
							235	750	90	700	550	50

Equivalents

C 10 B ER = CY 1 C	TW 1 Dar = CY 1	V 20 Tu = CY 1 C
E 20 U Mul = CY 1	TW 1 P Dar = CY 1	V 20 S Tu = CY 1
G 2080 Tri = CY 1	TW 10 Dar = CY 1 C	V 2018 Tu = CY 1
RE 2020 Vat = CY 1	UE 1 Oxt = CY 1	V 2118 Tu = CY 1 C
RS Fer = CY 1	UEG 51 Sat = CY 1	VEG 51 Sat = CY 1
RZ Fer = CY 1 C	UR 1 Mul = CY 1	13 U 6 Ult = CY 1
TCY 1 Tu = CY 1	UR 1 C Mul = CY 1 C	20 Y 1 TKD = CY 1
TV 1 P Dar = CY 1	UY 1 Dar = CY 1	

