



T.			$U_f$	$I_f$	$U_o$	$U_g$	$I_o$	$S$	$\mu$	$R_i$
			V	A	V	V	mA	mA/V	V/V	k $\Omega$
F 209	Phi	1	2,5	1,75	90	- 6	2,7	0,82	9	11
K 27	amer	2	2,5	1,75	250	-21	5,2	0,97	9	9,25
F 215	Phi	1	2,5	1,5	150	- 6	6,5	2	15	7,5
3 C 1	CCCP	3	2,5	1	220	- 4	8	2,2	22	10
4 C 1	amer	4	3	1,25	90	- 3	6	1	9,7	9,7
484	amer	2	3	1,25	180	- 9	6	1,35	12,5	9

### Equivalents

A 227	Vis = 27	TO-141	CCCP = 3 C 1	327	amer = 27
A 2200 W	Val = F 215	UY 227	amer = 27	401	amer = 4 C 1
ARX 2270	Tu = 27	UY 227 A	amer = 27	427	amer = 27
DE 1	amer = 27	UY 327	amer = 27	484 A	amer = 484
EY 627	amer = 27	UY 484	amer = 484	485	amer = 484
F 209 A	Phi = 27	4 C 1 A	amer = 4 C 1	2270	amer = 27
FR 503	amer = 27	27 S	amer = 27	3373	amer = 27
G 27	amer = 27	127	amer = 27	38027	amer = 27
N 27	amer = 27	227	amer = 27		

