SCAS005B - JULY 1987 - REVISED APRIL 1993


- Flow-Through Architecture Optimizes PCB Layout
- Center-Pin V<sub>CC</sub> and GND Configurations Minimize High-Speed Switching Noise
- EPIC<sup>™</sup> (Enhanced-Performance Implanted CMOS) 1-μm Process
- 500-mA Typical Latch-Up Immunity at 125°C
- Package Options Include Plastic Small-Outline Packages, Ceramic Chip Carriers, and Standard Plastic and Ceramic 300-mil DIPs

### description


These devices contain two independent 4-input AND gates. They perform the Boolean functions  $Y = A \cdot B \cdot C \cdot D$  or  $Y = \overline{A} + \overline{B} + \overline{C} + \overline{D}$  in positive logic.

The 54AC11021 is characterized for operation over the full military temperature range of -55°C to 125°C. The 74AC11021 is characterized for operation from -40°C to 85°C.

54AC11021 . . . J PACKAGE 74AC11021 . . . D OR N PACKAGE (TOP VIEW)



54AC11021 . . . FK PACKAGE (TOP VIEW)



NC - No internal connection

### FUNCTION TABLE (each gate)


, , ,										
	OUTPUT									
Α	В	С	D	Y						
Н	Н	Н	Н	Н						
L	Χ	Χ	Χ	L						
Χ	L	Χ	Χ	L						
Χ	Χ	L	Χ	L						
X	X	X	L	L						


EPIC is a trademark of Texas Instruments Incorporated.

SCAS005B - JULY 1987 - REVISED APRIL 1993

### logic symbol<sup>†</sup>

### logic diagram (positive logic)





Pin numbers shown are for the D, J, and N packages.

### absolute maximum ratings over operating free-air temperature range (unless otherwise noted)‡

Supply voltage range, V <sub>CC</sub>	$-0.5\ V$ to 7 $V$
Input voltage range, V <sub>I</sub> (see Note 1)	$\dots$ -0.5 V to V <sub>CC</sub> + 0.5 V
Output voltage range, V <sub>O</sub> (see Note 1)	$\dots$ -0.5 V to V <sub>CC</sub> + 0.5 V
Input clamp current, $I_{IK}$ ( $V_I < 0$ or $V_I > V_{CC}$ )	$\dots \dots \dots \pm 20 \; mA$
Output clamp current, I <sub>OK</sub> (V <sub>O</sub> < 0 or V <sub>O</sub> > V <sub>CC</sub> )	±50 mA
Continuous output current, $I_O(V_O = 0 \text{ to } V_{CC})$	±50 mA
Continuous current through V <sub>CC</sub> or GND	±100 mA
Storage temperature range	65°C to 150°C

<sup>‡</sup> Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTE 1: The input and output voltage ratings may be exceeded if the input and output clamp-current ratings are observed.

<sup>&</sup>lt;sup>†</sup> This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.

### recommended operating conditions

			54	1AC1102	1	74AC11021			
			MIN	NOM	MAX	MIN	NOM	MAX	UNIT
VCC	Supply voltage		3	5	5.5	3	5	5.5	V
		VCC = 3 V	2.1			2.1			
$V_{IH}$	High-level input voltage	V <sub>CC</sub> = 4.5 V	3.15			3.15			V
		V <sub>CC</sub> = 5.5 V	3.85			3.85			
V <sub>IL</sub>		V <sub>CC</sub> = 3 V			0.9			0.9	V
	Low-level input voltage	V <sub>CC</sub> = 4.5 V			1.35			1.35	
		V <sub>CC</sub> = 5.5 V			1.65			1.65	
٧ <sub>I</sub>	Input voltage	<u>.</u>	0		VCC	0		Vcc	V
٧o	Output voltage		0		VCC	0		Vcc	V
		V <sub>CC</sub> = 3 V			-4			-4	
loh	High-level output current	V <sub>CC</sub> = 4.5 V			-24			-24	mA
		V <sub>CC</sub> = 5.5 V			-24			-24	
lOL	Low-level output current	V <sub>CC</sub> = 3 V			12			12	
		V <sub>CC</sub> = 4.5 V			24			24	mA
		V <sub>CC</sub> = 5.5 V			24			24	
Δt/Δν	Input transition rise or fall rate	·	0		10	0		10	ns/V
TA	Operating free-air temperature		-55		125	-40		85	°C

# electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

	TEST CONDITIONS		T <sub>A</sub> = 25°C			54AC1	1021	74AC11021			
PARAMETER		VCC	MIN	TYP	MAX	MIN	MAX	MIN	MAX	UNIT	
		3 V	2.9			2.9		2.9			
	I <sub>OH</sub> = - 50 μA	4.5 V	4.4			4.4		4.4			
		5.5 V	5.4			5.4		5.4		٧	
	I <sub>OH</sub> = - 4 mA	3 V	2.58			2.4		2.48			
VOH		4.5 V	3.94			3.7		3.8			
	I <sub>OH</sub> = - 24 mA	5.5 V	4.94			4.7		4.8			
	$I_{OH} = -50 \text{ mA}^{\dagger}$	5.5 V				3.85					
	$I_{OH} = -75 \text{ mA}^{\dagger}$	5.5 V						3.85			
	I <sub>OL</sub> = 50 μA	3 V			0.1		0.1		0.1		
		4.5 V			0.1		0.1		0.1		
		5.5 V			0.1		0.1		0.1		
	I <sub>OL</sub> = 12 mA	3 V			0.36		0.5		0.44	.,	
VOL	1 24 mA	4.5 V			0.36		0.5		0.44	V	
	I <sub>OL</sub> = 24 mA	5.5 V			0.36		0.5		0.44		
	I <sub>OL</sub> = 50 mA <sup>†</sup>	5.5 V					1.65				
	I <sub>OL</sub> = 75 mA <sup>†</sup>	5.5 V							1.65		
IĮ	$V_I = V_{CC}$ or GND	5.5 V			±0.1		±1		±1	μΑ	
ICC	$V_I = V_{CC}$ or GND, $I_O = 0$	5.5 V			4		80		40	μΑ	
C <sub>i</sub>	$V_I = V_{CC}$ or GND	5 V		3.5						pF	

<sup>†</sup> Not more than one output should be tested at a time, and the duration of the test should not exceed 10 ms.



SCAS005B - JULY 1987 - REVISED APRIL 1993

## switching characteristics over recommended operating free-air temperature range, $V_{CC}$ = 3.3 V $\pm$ 0.3 V (unless otherwise noted) (see Figure 1)

PARAMETER	FROM	то	T,	<sub>A</sub> = 25°C	;	54AC1	11021	74AC1	1021	
	(INPUT)	(OUTPUT)	MIN	TYP	MAX	MIN	MAX	MIN	MAX	UNIT
t <sub>PLH</sub>	Any	V	1.5	8.2	11.4	1.5	13.9	1.5	13	20
<sup>t</sup> PHL	Any	ſ	1.5	6.4	8.7	1.5	9.9	1.5	9.3	ns


## switching characteristics over recommended operating free-air temperature range, $V_{CC}$ = 5 V $\pm$ 0.5 V (unless otherwise noted) (see Figure 1)

DADAMETED	FROM	то	T,	4 = 25°C	;	54AC1	11021	74AC1	1021	
PARAMETER	(INPUT)	(OUTPUT)	MIN	TYP	MAX	MIN	MAX	MIN	MAX	UNIT
t <sub>PLH</sub>	Any	V	1.5	5.6	7.8	1.5	9.4	1.5	8.8	20
<sup>t</sup> PHL	Any	Y	1.5	4.6	6.5	1.5	7.4	1.5	6.9	ns

### operating characteristics, V<sub>CC</sub> = 5 V, T<sub>A</sub> = 25°C

	PARAMETER	TEST CONDITIONS	TYP	UNIT
C <sub>pd</sub>	Power dissipation capacitance per gate	$C_L = 50 \text{ pF},  f = 1 \text{ MHz}$	38	pF

#### PARAMETER MEASUREMENT INFORMATION



NOTES: A. C<sub>I</sub> includes probe and jig capacitance.

- B. Input pulses are supplied by generators having the following characteristics: PRR  $\leq$  10 MHz,  $Z_O = 50 \ \Omega$ ,  $t_f = 3 \ ns$ ,  $t_f = 3 \ ns$ .
- C. The outputs are measured one at a time with one input transition per measurement.

Figure 1. Load Circuit and Voltage Waveforms

### **IMPORTANT NOTICE**

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

**Applications Products Amplifiers** amplifier.ti.com Audio www.ti.com/audio Data Converters Automotive www.ti.com/automotive dataconverter.ti.com DLP® Products Broadband www.dlp.com www.ti.com/broadband DSP Digital Control dsp.ti.com www.ti.com/digitalcontrol Clocks and Timers www.ti.com/clocks Medical www.ti.com/medical Military Interface www.ti.com/military interface.ti.com Optical Networking Logic logic.ti.com www.ti.com/opticalnetwork Power Mgmt power.ti.com Security www.ti.com/security Telephony Microcontrollers microcontroller.ti.com www.ti.com/telephony Video & Imaging www.ti-rfid.com www.ti.com/video RF/IF and ZigBee® Solutions www.ti.com/lprf Wireless www.ti.com/wireless

> Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2009, Texas Instruments Incorporated