NTJD4158C

Small Signal MOSFET

30 V/-20 V, +0.25/-0.88 A, Complementary, SC-88

Features

- Leading 20 V Trench for Low R_{DS(on)} Performance
- ESD Protected Gate
- SC-88 Package for Small Footprint (2 x 2 mm)
- This is a Pb-Free Device

Applications

- DC-DC Conversion
- Load/Power Management
- Load Switch
- Cell Phones, MP3s, Digital Cameras, PDAs

MAXIMUM RATINGS (T_{.I} = 25°C unless otherwise noted)

INDUMONITATION (1) = 20 0 diliono otto incom						
Parameter			Symbol	Value	Unit	
Drain-to-Source Volt	N-Ch	V_{DSS}	30	V		
				-20		
Gate-to-Source Volta	N-Ch	V_{GS}	±20	V		
				±12		
N-Channel Continuous Drain	Steady	T _A = 25°C	I _D	0.25	Α	
Current (Note 1)	State	T _A = 85°C		0.18		
P-Channel Continuous Drain	Steady	T _A = 25°C	1	-0.88		
Current (Note 1)	State	T _A = 85°C	1	-0.63		
Power Dissipation (Note 1)	Steady State	T _A = 25°C	P _D	0.27	W	
Pulsed Drain Cur- N-Ch		t- 10	I _{DM}	0.5	Α	
rent	P-Ch	tp = 10 μs		-3.0	1	
Operating Junction and Storage Temperature			T _J , T _{stg}	–55 to 150	°C	
Source Current (Body	N-Ch	I _S	0.25	Α		
	P-Ch		-0.48			
Lead Temperature for Soldering Purposes (1/8" from case for 10 s)			TL	260	°C	

THERMAL RESISTANCE RATINGS

Parameter	Symbol	Max	Unit	
Junction-to-Ambient - Steady State (Note 1)	$R_{\theta JA}$	460	°C/W	

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

1. Surface mounted on FR4 board using 1 in sq pad size (Cu area = 1.127 in sq [1 oz] including traces).




ON Semiconductor®

http://onsemi.com

V _{(BR)DSS}	R _{DS(on)} Typ	I _D Max
N-Ch	1.0 Ω @ 4.5 V	0.25 A
30 V	1.5 Ω @ 2.5 V	0.25 A
P-Ch	215 mΩ @ -4.5 V	-0.88 A
–20 V	345 mΩ @ –2.5 V	-0.00 A






MARKING DIAGRAM & PIN ASSIGNMENT



SC-88 (SOT-363) CASE 419B STYLE 26



TCD = Specific Device Code

(Note: Microdot may be in either location)

ORDERING INFORMATION

Device	Package	Shipping†		
NTJD4158CT1G	SC-88 (Pb-Free)	3000 Tape & Reel		

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specification Brochure, BRD8011/D.


NTJD4158C

ELECTRICAL CHARACTERISTICS (T_{.1} = 25°C unless otherwise noted)

Parameter	Symbol	N/P	Test Condition		Min	Тур	Max	Unit
OFF CHARACTERISTICS (Note 3)								
Drain-to-Source	V _{(BR)DSS}	N		I _D = 250 μA	30			V
Breakdown Voltage	- (DU)D99	P	$V_{GS} = 0 V$	$I_D = -250 \mu\text{A}$	-20			1
Drain-to-Source Breakdown	V _{(BR)DSS} /	N		10 = 200 μα τ		33		mV/
Voltage Temperature Coefficient	TJ	P				-9.0		°C
Zero Gate Voltage Drain Current	I _{DSS}	N	V _{GS} = 0 V, V _{DS} = 30 V			0.0	1.0	μA
Zoro diato romago Zrami oumom	.033	P	$V_{GS} = 0 \text{ V}, V_{DS} = -16 \text{ V}$	$T_J = 25^{\circ}C$			1.0	μ. 1
		N	$V_{GS} = 0 \text{ V}, V_{DS} = 30 \text{ V}$			0.5	1.0	
		P	$V_{GS} = 0 \text{ V}, V_{DS} = -16 \text{ V}$	$T_{\rm J} = 125^{\circ}{\rm C}$		0.5		
Gate-to-Source Leakage Current	I _{GSS}	N	$V_{DS} = 0 \text{ V}, V_{GS} = 0 \text{ V}$	10 V			1.0	μA
	-033	P	V _{DS} = 0 V, V _{GS} = -				1.0	,
ON CHARACTERISTICS (Note 2)			100 - 1, 100					
Gate Threshold Voltage	V _{GS(TH)}	N		I _D = 100 μA	0.8	1.2	1.5	V
3	G5(111)	P	$V_{GS} = V_{DS}$	$I_{D} = -250 \mu\text{A}$	-0.45			
Negative Gate Threshold	V _{GS(TH)} /	N		1.D 200 part	51.15	3.2		mV/
Temperature Coefficient	TJ	Р				-2.7		°C
Drain-to-Source On Resistance	R _{DS(on)}	N	V _{GS} = 4.5 V, I _D = 1	0 mA		1.0	1.5	Ω
	D3(011)	P	$V_{GS} = -4.5 \text{ V}, I_D = -4.5 \text{ V}$			0.215	0.260	1 -
		N	$V_{GS} = 2.5 \text{ V}, I_D = 10$			1.5	2.5	
		Р	$V_{GS} = -2.5 \text{ V}, I_D = -$			0.345	0.500	
Forward Transconductance	9 _{FS}	N	$V_{DS} = 3.0 \text{ V}, I_D = 10$			0.08		S
	313	Р	$V_{DS} = -10 \text{ V}, I_D = -0$			3.0		
CHARGES, CAPACITANCES AND	GATE RESIS	TANC						
Input Capacitance	C _{ISS}	N	_	V _{DS} = 5.0 V		20	33	pF
mpar Sapasitarios	9188	P		$V_{DS} = -20 \text{ V}$		155	225	Ρ'
Output Capacitance	C _{OSS}	N		$V_{DS} = -20 \text{ V}$ $V_{DS} = 5.0 \text{ V}$		19	32	
	C _{RSS}	P	$f = 1 MHz$, $V_{GS} = 0 V$	$V_{DS} = -20 \text{ V}$		25	40	
Reverse Transfer Capacitance		N		$V_{DS} = 5.0 \text{ V}$		7.25	12	
Treverse Transfer Supusitance	CHSS	P		$V_{DS} = -20 \text{ V}$		18	30	
Total Gate Charge	Q _{G(TOT)}	N	$V_{GS} = 5.0 \text{ V}, V_{DS} = 24 \text{ V}, I_D = 0.1 \text{ A}$			0.9	1.5	nC
Total date offarge	46(101)	P	$V_{GS} = -4.5 \text{ V}, V_{DS} = -10 \text{ V}, I_D = -0.88 \text{ A}$			2.2	3.5	1.0
Threshold Gate Charge	Q _{G(TH)}	N		$V_{GS} = -4.3 \text{ V}, V_{DS} = -10 \text{ V}, I_D = -0.66 \text{ A}$ $V_{GS} = 5.0 \text{ V}, V_{DS} = 24 \text{ V}, I_D = 0.1 \text{ A}$		0.2	0.0	
·····se···sia sians sinaige	~G(1H)	P	$V_{GS} = -4.5 \text{ V}, V_{DS} = -10 \text{ V},$			0.2		
Gate-to-Source Charge	Q _{GS}	N	$V_{GS} = 5.0 \text{ V}, V_{DS} = 24 \text{ V},$			0.3		ł
ciano to comico cinange	~u3	P	$V_{GS} = -4.5 \text{ V}, V_{DS} = -10 \text{ V},$			0.5		
Gate-to-Drain Charge	Q _{GD}	N	$V_{GS} = 5.0 \text{ V}, V_{DS} = 24 \text{ V},$			0.2		ł
3	·GD	Р	$V_{GS} = -4.5 \text{ V}, V_{DS} = -10 \text{ V},$			0.65		
SWITCHING CHARACTERISTICS (I	Note 3)		<u>, </u>	, <u>J</u>				•
Turn-On Delay Time	t _{d(ON)}	N				15		ns
Rise Time	t _r	1	V _{GS} = 4.5 V, V _{DD} = 5.0 V,			66		1
Turn-Off Delay Time	t _{d(OFF)}	1	$V_{GS} = 4.5 \text{ V}, V_{DD} = 5.0 \text{ V},$ $I_{D} = 250 \text{ mA}, R_{G} = 50 \Omega$			56		1
Fall Time	t _f	1				78		1
Turn-On Delay Time	t _{d(ON)}	Р				5.8		1
•		1	$V_{GS} = -4.5 \text{ V}, V_{DD} = -10 \text{ V},$ $I_D = -0.5 \text{ A}, R_G = 20 \Omega$			6.5		1
Rise Time	t _r					13.5		1
Rise Time Turn-Off Delay Time				20 Ω		13.5		1
	t _r t _{d(OFF)} t _f			20 Ω		3.5		
Turn-Off Delay Time	t _{d(OFF)}			20 Ω				
Turn-Off Delay Time Fall Time	t _{d(OFF)} t _f FERISTICS	N	$I_D = -0.5 \text{ A}, R_G = 2$				0.7	l v
Turn-Off Delay Time Fall Time DRAIN-SOURCE DIODE CHARACT	t _{d(OFF)}	N P		$I_S = 10 \text{ mA}$ $I_S = -0.48 \text{ A}$		3.5	0.7	V
Turn-Off Delay Time Fall Time DRAIN-SOURCE DIODE CHARACT	t _{d(OFF)} t _f FERISTICS		$I_D = -0.5 \text{ A}, R_G = 2$ $V_{GS} = 0 \text{ V}, T_J = 25^{\circ}\text{C}$	$I_S = 10 \text{ mA}$ $I_S = -0.48 \text{ A}$		3.5 0.65		V
Turn-Off Delay Time Fall Time DRAIN-SOURCE DIODE CHARACT	t _{d(OFF)} t _f FERISTICS	Р	$I_D = -0.5 \text{ A}, R_G = 2$	$I_S = 10 \text{ mA}$ $I_S = -0.48 \text{ A}$ $I_S = 10 \text{ mA}$		3.5 0.65 -0.8		V
Turn-Off Delay Time Fall Time DRAIN-SOURCE DIODE CHARACT	t _{d(OFF)} t _f FERISTICS	P N	$I_D = -0.5 \text{ A}, R_G = 2$ $V_{GS} = 0 \text{ V}, T_J = 25^{\circ}\text{C}$	$I_S = 10 \text{ mA}$ $I_S = -0.48 \text{ A}$		3.5 0.65 -0.8 0.45		V

Pulse Test: pulse width ≤ 300 μs, duty cycle ≤ 2%.
 Switching characteristics are independent of operating junction temperatures.


TYPICAL N-CHANNEL PERFORMANCE CURVES (T_J = 25°C unless otherwise noted)



0.2 V_{DS} = 5 V 0.15 V_{DS} = 5 V T_J = 125°C T_J = -55°C 1 1.25 1.5 1.75 2 2.25 2.5 V_{GS}, GATE-TO-SOURCE VOLTAGE (VOLTS)

Figure 1. On-Region Characteristics

Figure 2. Transfer Characteristics







Figure 3. On-Resistance vs. Drain Current and Temperature

Figure 4. On-Resistance vs. Drain Current and Gate Voltage







Figure 5. On–Resistance Variation with Temperature

Figure 6. Drain-to-Source Leakage Current vs. Voltage

TYPICAL N-CHANNEL PERFORMANCE CURVES ($T_J = 25^{\circ}C$ unless otherwise noted)



GATE-TO-SOURCE OR DRAIN-TO-SOURCE VOLTAGE (VOLTS)

Figure 7. Capacitance Variation




Figure 8. Gate-to-Source Voltage vs. Total Gate Charge




Figure 9. Resistive Switching Time Variation vs. Gate Resistance




Figure 10. Diode Forward Voltage vs. Current

TYPICAL P-CHANNEL PERFORMANCE CURVES (T_J = 25°C unless otherwise noted)




Figure 1. On-Region Characteristics




Figure 2. Transfer Characteristics




Figure 3. On-Resistance vs. Drain Current and Temperature




Figure 4. On-Resistance vs. Drain Current and Gate Voltage




Figure 5. On–Resistance Variation with Temperature





Figure 6. Drain-to-Source Leakage Current vs. Voltage

TYPICAL P-CHANNEL PERFORMANCE CURVES ($T_J = 25^{\circ}C$ unless otherwise noted)



GATE-TO-SOURCE OR DRAIN-TO-SOURCE VOLTAGE (VOLTS)

Figure 7. Capacitance Variation




Figure 9. Resistive Switching Time Variation vs. Gate Resistance




Figure 8. Gate-to-Source Voltage vs. Total Gate Charge





Figure 10. Diode Forward Voltage vs. Current

NTJD4158C

PACKAGE DIMENSIONS

SC-88/SC70-6/SOT-363 CASE 419B-02 **ISSUE W**



NOTES:

- 1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
- CONTROLLING DIMENSION: INCH.
- 419B-01 OBSOLETE, NEW STANDARD 419B-02.


	MILLIMETERS			INCHES			
DIM	MIN	NOM	MAX	MIN	NOM	MAX	
Α	0.80	0.95	1.10	0.031	0.037	0.043	
A1	0.00	0.05	0.10	0.000	0.002	0.004	
А3		0.20 REF			0.008 REF		
b	0.10	0.21	0.30	0.004	0.008	0.012	
С	0.10	0.14	0.25	0.004	0.005	0.010	
D	1.80	2.00	2.20	0.070	0.078	0.086	
Е	1.15	1.25	1.35	0.045	0.049	0.053	
е		0.65 BSC 0.026 BSC			С		
L	0.10	0.20	0.30	0.004	0.008	0.012	
HE	2.00	2.10	2.20	0.078	0.082	0.086	

STYLE 26:

- PIN 1. SOURCE 1 2. GATE 1

 - 3. DRAIN 2
 - 4. SOURCE 2 5 GATE 2
 - 6. DRAIN 1

SOLDERING FOOTPRINT*



*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

ON Semiconductor and 👊 are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice on semiconductor and ware registered readerlanks of semiconductor Components industries, ICC (SCILLC) solice (SCILC). Solice these west literapplic to make so the charges without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specificalized can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA **Phone**: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free USA/Canada

Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81-3-5773-3850

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative