

18-Line Low Capacitance SCSI Active Terminator

FEATURES

- Complies with SCSI, SCSI-2 and SPI-2 Standards
- 6pF Channel Capacitance during Disconnect
- 100µA Supply Current in Disconnect Mode
- Meets SCSI Hot Plugging Capability
- –650mA Sourcing Current for Termination
- +200mA Sinking Current for Active Negation
- Provides Active Termination for 18 Lines
- Logic Command Disconnects all Termination Lines
- Trimmed Termination Current to 5%
- Trimmed Impedance to 5%
- Current Limit and Thermal Shutdown
 Protection

DESCRIPTION

The UC5608 provides 18 lines of active termination for a SCSI (Small Computer Systems Interface) parallel bus. The SCSI standard recommends active termination at both ends of the bus cable.


The UC5608 is pin-for-pin compatible with its predecessors, the UC5601 and UC5602 - 18 Line Active Terminator. Parametrically the UC5608 has a 5% tolerance on impedance and current compared to a 3% tolerance on the UC5601 and the sink current is increased from 20 to 200mA. The low side clamps have been removed. Custom power packages are utilized to allow normal operation at full power conditions (2 Watts).

When in disconnect mode the terminator will disconnect all terminating resistors and disable the regulator, greatly reducing standby power. The output channels remain high impedance even without Termpwr applied.

Internal circuit trimming is utilized to trim the impedance to a 5% tolerance and, most importantly, to trim the output current to a 5% tolerance, as close to the max SCSI spec as possible, which maximizes noise margin in fast SCSI operation.

Other features include 4.0 to 5.25V Termpwr, thermal shutdown and current limit.

This device is offered in low thermal resistance versions of the industry standard 28 pin wide body SOIC, 28 pin wide body TSSOP, and 28 pin PLCC, as well as 24 pin DIP.



BLOCK DIAGRAM


ABSOLUTE MAXIMUM RATINGS

Termpwr Voltage
Signal Line Voltage 0V to +7V
Regulator Output Current
Storage Temperature
Operating Temperature
Lead Temperature (Soldering, 10 Sec.)
Unless otherwise specified all voltages are with respect to Ground. Currents are posi-
tive into, negative out of the specified terminal.
Consult Packaging Section of Unitrode Integrated Circuits databook for thermal limita-
tions and considerations of packages.


RECOMMENDED OPERATING CONDITIONS

Termpwr Voltage	3V to 5.25V
Signal Line Voltage	0V to +5V
Disconnect Input Voltage 0V t	to Termpwr


CONNECTION DIAGRAMS




* QP package pins 12 - 18 serve as both heatsink and signal ground.



* DWP package pin 28 serves as signal ground; pins 7, 8, 9, 20, 21, 22 serve as heatsink/ground.





r		
DIL-24 (Top View N or J Package)	
	\bigcirc	
DISCNCT 1		24 GND
LINE1 2		23 LINE18
LINE2 3		22 LINE17
N/C 4		21 N/C
LINE3 5		20 LINE16
LINE4 6		19 LINE15
LINE5 7		18 LINE14
LINE6 8		17 LINE13
LINE7 9		16 LINE12
LINE8 10		15 LINE11
LINE9 11		14 LINE10
TRMPWR 12		13 REG

Note: Drawings are not to scale.

ELECTRICAL CHARACTERISTICS Unless otherwise stated, these specifications apply for TA = 0°C to 70°C. TRMPWR =
4.75V, DISCNCT = Ground. TA = TJ.

PARAMETER	TEST CONDITIONS				TYP	MAX	UNITS
Supply Current Section							
Termpwr Supply Current All termination lines = Open					17	25	mA
	All termination lines = $0.5V$				400	430	mA
Power Down Mode	DISCNCT = Open				100	150	μA
Output Section (Terminator Lines	s)						
Terminator Impedance	Δ ILINE = -5mA to -15mA			104.5	110	115.5	Ohms
Output High Voltage	VTRMPWR = 4V (Note 1)		2.65	2.9	3.0	V
Max Output Current			$T_J = 25^{\circ}C$	-20.3	-21.5	-22.4	mA
			$0^{\circ}C < T_J < 70^{\circ}C$	-19.8	-21.5	-22.4	mA
Max Output Current V	VLINE = $0.5V$, TF	VLINE = 0.5V, TRMPWR = 4V (Note 1)		-19.5	-21.5	-22.4	mA
				-19.0	-21.5	-22.4	mA
	VLINE = $0.2V$, TF	VLINE = 0.2V, TRMPWR = 4V to 5.25V		-21.6	-24.0	-25.4	mA
Output Leakage	DISCNCT = 4V	TRMPWR = 0V to 5.25V	VLINE = 0 to 4V		10	400	nA
		REG = 0V	VLINE = 5.25V			100	μA
		TRMPWR = $0V$ to 5.25V, VLINE = $0V$ to 5.25V	REG = Open		10	400	nA
Output Capacitance	DISCNCT = Open (Note 2)				6	7	pF
Regulator Section							
Regulator Output Voltage				2.8	2.9	3	V
Regulator Output Voltage	All Termination Lines = 4V		2.8	2.9	3	V	
Line Regulation	TRMPWR = 4V to 6V			10	20	mV	
Drop Out Voltage	All Termination Lines = 0.5V			1.0	1.2	V	
Short Circuit Current	VREG = 0V		-450	-650	-950	mA	
Sinking Current Capability	VREG = 3.5V		100	200	500	mA	
Thermal Shutdown					170		°C
Thermal Shutdown Hysteresis				10		°C	
Disconnect Section							
Disconnect Threshold				1.1	1.4	1.7	V

Note 1: Measuring each termination line while other 17 are low (0.5V). Note 2: Guaranteed by design. Not 100% tested in production.

APPLICATION INFORMATION




Figure 1: Typical SCSI Bus Configuration

UNITRODE CORPORATION 7 CONTINENTAL BLVD. • MERRIMACK, NH 03054 TEL. (603) 424-2410 • FAX (603) 424-3460

IMPORTANT NOTICE

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgement, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its semiconductor products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

CERTAIN APPLICATIONS USING SEMICONDUCTOR PRODUCTS MAY INVOLVE POTENTIAL RISKS OF DEATH, PERSONAL INJURY, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE ("CRITICAL APPLICATIONS"). TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS. INCLUSION OF TI PRODUCTS IN SUCH APPLICATIONS IS UNDERSTOOD TO BE FULLY AT THE CUSTOMER'S RISK.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, warranty or endorsement thereof.

Copyright © 1999, Texas Instruments Incorporated