

SBA50-09J

Schottky Barrier Diode (Twin Type · Cathode Common)

90V, 5A Rectifier

Applications

· High frequency rectification (switching regulators, converters, choppers).


Features

- · Low forward voltage (V_F max=0.75V).
- · Fast reverse recovery time.
- · Low switching noise.
- · High reliability due to highly reliable planar structure.
- · Micaless package facilitating easy mounting.

Package Dimensions

unit:mm

1178A



Specifications

Absolute Maximum Ratings at Ta = 25°C


Parameter	Symbol	Conditions	Ratings	Unit
Repetitive Peak Reverse Voltage	V _{RRM}		90	V
Nonrepetitive Peak Reverse Surge Voltage	VRSM		95	V
Average Output Current	I _O	50Hz, resistive load, Tc=94°C	5	Α
Surge Forward Current	I _{FSM}	50Hz sine wave, 1 cycle	60	Α
Junction Temperature	Tj		-55 to +125	°C
Storage Temperature	Tstg		-55 to +125	°C


Electrical Characteristics

Parameter	Symbol	Conditons	Ratings			Unit
			min	typ	max	Offic
Reverse Voltage	V _R	I _R =1mA, Tj=25°C, *	90			V
Forward Voltage	٧F	I _F =2.5A, Tj=25°C, *			0.75	V
Reverse Current	IR	V _R =45V, Tj=25°C, *			0.1	mA
Interterminal Capacitance	С	V _R =10V, Tj=25°C, *		90		pF
Thermal Resistance	Rth(j-c)	Junction-Case:Smoothed DC			5.0	°C/W

Note*:Value per element

Electrical Connection





- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
 - ② Not impose any responsibilty for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of April, 1998. Specifications and information herein are subject to change without notice.