

Wskaźnik dostrojenia


**EM 85**

Lorenz

Nowal

EM85

$$\frac{U_j = 6.3V}{I_z = 300mA}$$



Wartości charakterystyczne i robocze

$U_{ab}$	250	V
$U_{s1}$	0...—18	V
$I_a$	0,5...0,12	mA
$I_L$	2,1	mA
$R_a$	500	k $\Omega$
$\beta$	100°...0°	
$h$	1	%

Wartości graniczne

$I_k$	6	mA
$P_{a\max}$	0,5	W
$U_{a\max}$	300	V
$U_{L\max}$	300	V
$U_{L\min}$	100	V
$R_{s1}$	3	M $\Omega$

TYPY PODOBNE

