

# New Jersey Semi-Conductor Products, Inc.

20 STERN AVE.  
SPRINGFIELD, NEW JERSEY 07081  
U.S.A.

TELEPHONE: (973) 376-2922  
(212) 227-6005  
FAX: (973) 376-8960

2N6716 2N6717 2N6718 NPN  
2N6728 2N6729 2N6730 PNP

## COMPLEMENTARY SILICON POWER TRANSISTORS

T0-237

MAXIMUM RATINGS ( $T_A=25^\circ\text{C}$  unless otherwise noted)

	<u>SYMBOL</u>	<u>2N6716</u> <u>2N6728</u>	<u>2N6717</u> <u>2N6729</u>	<u>2N6718</u> <u>2N6730</u>	<u>UNIT</u>
Collector-Base voltage	$V_{CBO}$	60	80	100	V
Collector-Emitter Voltage	$V_{CEO}$	60	80	100	V
Emitter-Base Voltage	$V_{EBO}$		5.0		V
Collector Current	$I_C$		2.0		A
Base Current	$I_B$		0.5		A
Power Dissipation	$P_D$		1.0		W
Power Dissipation ( $T_C=25^\circ\text{C}$ )	$P_D$		2.0		W
Operating and Storage					
Junction Temperature	$T_J, T_{stg}$		-65 TO +150		$^\circ\text{C}$
Thermal Resistance	$\theta_{JA}$		125		$^\circ\text{C}/\text{W}$
Thermal Resistance	$\theta_{JC}$		62.5		$^\circ\text{C}/\text{W}$

ELECTRICAL CHARACTERISTICS ( $T_A=25^\circ\text{C}$ )

<u>SYMBOL</u>	<u>TEST CONDITIONS</u>	<u>MIN</u>	<u>MAX</u>	<u>UNIT</u>
$I_{CBO}$	$V_{CB}=\text{Rated } V_{CBO}$		0.1	$\mu\text{A}$
$I_{EBO}$	$V_{EB}=\text{Rated } V_{EBO}$		10	$\mu\text{A}$
$BV_{CBO}$	$I_C=0.1\text{mA}$ (2N6716, 2N6728)	60		V
$BV_{CBO}$	$I_C=0.1\text{mA}$ (2N6717, 2N6729)	80		V
$BV_{CBO}$	$I_C=0.1\text{mA}$ (2N6718, 2N6730)	100		V
$BV_{CEO}$	$I_C=1.0\text{mA}$ (2N6716, 2N6728)	60		V
$BV_{CEO}$	$I_C=1.0\text{mA}$ (2N6717, 2N6729)	80		V
$BV_{CEO}$	$I_C=1.0\text{mA}$ (2N6718, 2N6730)	100		V
$BV_{EBO}$	$I_E=0.1\text{mA}$	5.0-		V
$V_{CE(SAT)}$	$I_C=250\text{mA}, I_B=10\text{mA}$		0.5	V
$V_{BE(ON)}$	$V_{CE}=1.0\text{V}, I_C=250\text{mA}$		1.2	V
$h_{FE}$	$V_{CE}=1.0\text{V}, I_C=50\text{mA}$	80		
$h_{FE}$	$V_{CE}=1.0\text{V}, I_C=250\text{mA}$	50	250	V
$f_T$	$V_{CE}=5.0\text{V}, I_C=200\text{mA}, f=20\text{MHz}$	50	500	MHz
$C_{ob}$	$V_{CB}=10\text{V}, I_E=0, f=1.0\text{MHz}$	30		pF

NJ Semi-Conductors reserves the right to change test conditions, parameters limits and package dimensions without notice. Information furnished by NJ Semi-Conductors is believed to be both accurate and reliable at the time of going to press. However NJ Semi-Conductors assumes no responsibility for any errors or omissions discovered in its use. NJ Semi-Conductors encourages customers to verify that datasheets are current before placing orders.

Quality Semi-Conductors

